

User Manual

USB outputs

Using one port

- USB Type-C® port 1/2: 100 W max (5 V/3 A, 9 V/3 A, 12 V/3 A, 15 V/3 A, 20 V/5 A)
- USB Type-C® port 3/USB-A port 1: 18 W max (5 V/3 A, 9 V/2 A, 12 V/1.5 A)

Using two ports simultaneously

- C1 + C2: 100 W max in total (C1: 65 W (5 V/3 A, 9 V/3 A, 12 V/3 A, 15 V/3 A, 20 V/3.25 A) + C2: 35 W (5 V/3 A, 9 V/3 A, 12 V/2.91 A, 15 V/2.33 A, 20 V/1.75 A))
- C1/C2 + C3/A1: 83 W max in total (C1/C2: 65 W (5 V/3 A, 9 V/3 A, 12 V/3 A, 15 V/3 A, 20 V/3.25 A) + C3/A1: 18 W (5 V/3 A, 9 V/2 A, 12 V/1.5 A))
- C3 + A1: 15 W max in total (C3/A1: 15 W (5 V/3 A))

Using three ports simultaneously

- C1 + C2 + C3/A1: 103 W max in total (C1: 65 W (5 V/3 A, 9 V/3 A, 12 V/3 A, 15 V/3 A, 20 V/3.25 A) + C2: 20 W (5 V/3 A, 9 V/2.22 A, 12 V/1.67 A) + C3/A1: 18 W (5 V/3 A, 9 V/2 A, 12 V/1.5 A))
- C1/C2 + C3 + A1: 80 W max in total (C1/C2: 65 W (5 V/3 A, 9 V/3 A, 12 V/3 A, 15 V/3 A, 20 V/3.25 A) + C3/A1: 15 W (5 V/3 A))

Using four ports simultaneously

- C1 + C2 + C3 + A1: 100 W max in total (C1: 65 W (5 V/3 A, 9 V/3 A, 12 V/3 A, 15 V/3 A, 20 V/3.25 A) + C2: 20 W (5 V/3 A, 9 V/2.22 A, 12 V/1.67 A) + C3/A1: 15 W (5 V/3 A))

**WARNING**

Ignoring these precautions may lead to inappropriate handling that may cause death or serious injuries.

**CAUTION**


Ignoring these precautions may lead to inappropriate handling that may cause serious injuries or property damage.

Be sure to read the precautions described here to prevent injury, malfunction, fire, and other accidents.

How to replace the fuse

If the AC outlet can no longer be used, the fuse may have blown. Remove the blown fuse from the fuse box, and be sure to eliminate the cause of the blown fuse before replacing it with a spare fuse (B51362).

*The fuse does not affect USB operation.

**WARNING**

- Ensure that the electrical devices you connect do not exceed the power capacity (rating) indicated on the product. Exceeding the power capacity (rating) may cause a fire or malfunction.
- If the product is accidentally soaked in liquids such as detergents or insecticides, replace it with a new one. Not doing so may cause insulation failure or metal corrosion and is extremely dangerous.
- Never disassemble or modify the product.

- Do not spill liquid cleaners such as toilet cleaners onto the plug.
- Do not overload the outlet by connecting multiple plugs or power strips. Doing so may cause a fire.
- Some devices prohibit the use of power strips. For details, check the user manuals of the connected devices.
- Clean the outlet and plug blades regularly to prevent dust buildup. Not doing so may cause electrical leakage or fire.

**CAUTION**

- The product supports Type A, G(BF), I(O), and C outlets. If you intend to use electrical devices incompatible with overseas voltage, prepare a transformer separately.
- Electrical devices with a current consumption exceeding 10 A cannot be used. Always check the rated specifications.
- Do not use plugs with bent blades.
- Do not use the product in locations where it may be exposed to water.
- Before using this product, check that there is no foreign matter such as dust or liquid in the connectors of the product and the connected device. Especially for a waterproof device, check for remaining water when connecting it after it gets wet. Charging when the connector is wet or has foreign matter in it may cause a fire, electric shock, or malfunction.
- Do not drop the product, subject it to strong shocks, or place objects on it.
- Do not use the product outdoors. The product is designed for indoor use only.

- When the connected electrical devices are not in use, unplug the product and the devices.
- Insert the plug properly to ensure firm contact with the outlet. Do not use the plug if the plug blades are deformed or if the connection is loose. Doing so may cause electrical leakage or fire.
- Keep the product out of reach of young children when in use.
- Do not use the product with devices that operate continuously.
- Do not stack two units of the product.
- Do not insert or remove the plug, or operate the switch lever, with wet hands.
- Always turn off the electrical devices before inserting or removing the plug.
- Do not use an incompatible charging cable. Doing so may cause a fire, melting, or malfunction.
- Do not use or store the product in locations exposed to direct sunlight, high temperatures, high humidity, or excessive moisture, dust, or vibration. Doing so may cause a fire, electric shock, or malfunction.

For safe use

- The product is a consumable item. Inspect it at least once a year, and if any abnormalities are found, replace it with a new one.
- If any part of the product becomes abnormally hot while electrical devices are in use, replace it with a new one.

- If the plug blades are deformed or significantly discolored, or if the outlet is burned or chipped, replace the product with a new one.

Compliance Status

www.elecom.co.jp/global/certification/

Model: T-TA01-AS100BK

Global Support

A customer who purchases outside Japan should contact the local retailer in the country of purchase for inquiries. In "ELECOM CO., LTD. (Japan)", no customer support is available for inquiries about purchases or usage in/from any countries other than Japan. Also, no language other than Japanese is available. Replacements will be made under stipulation of the ELECOM warranty.

<https://www.elecom.co.jp/r/s536>

**Limitation of Liability**

- In no event will ELECOM Co., Ltd. be liable for any lost profits or special, consequential, indirect, punitive damages arising out of the use of this product.
- ELECOM Co., Ltd. will have no liability for any loss of data, damages, or any other problems that may occur to any devices connected to this product.

ELECOM CO., LTD.

Fushimimachi 4-1-1, Chuo-ku, Osaka City
www.elecom.co.jp/global/

- ELECOM CO., LTD. owns the copyright of this manual.
- Unauthorized copying and/or reproducing of all or part of this manual is prohibited.
- If you have any concerns or question regarding this manual, please contact the retailer from whom you purchased this product.
- We shall bear no responsibility for any device failure or malfunction of other devices resulting from the use of this product.
- The images are for illustration purposes only and may differ from your actual product.
- In order to make improvements to this product and for improved safety, the colors and specifications are subject to change without prior notice.
- The company and product names on the packaging and the manual are, in general, trademarks or registered trademarks of their respective companies.
- Lightning is a trademark of Apple Inc., registered in the U.S. and other countries.
- USB Type-C® and USB-C® are registered trademarks of USB Implementers Forum.

Travel Adapter

Manual, Safety precautions and Compliance with regulations, 1st edition, June, 2026