


※本製品に接続するケーブルは、ご使用になる機器に合わせて別途ご用意ください。  
※USB Type-C、Lightning以外の端子に変換するケーブルや変換アダプターを使用すると、給電(充電)できない場合や、充電が遅くなる場合があります。  
※本製品使用中に、空いているポートに別の機器を接続した際など、接続中のポートの出力が一時的に切れ再接続することがあります。再度スマホなどから充電開始音が鳴る場合がありますが、故障ではありません。

## 使用方法

- 1.本製品に充電ケーブルを接続し、もう片方のコネクタを充電したい機器に接続します。
- 2.電源プラグを起し、家庭用コンセントに挿し込むと充電を開始します。



## 製品仕様

|       |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   |     |       |
|-------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|-----|-------|
| ポート形状 | USB Type-Cポート×2・USB-Aポート×1                                                                                                                                                                                                                                                                                                                                                                                                                                                        |     |       |
| 寸法    | [幅]約66mm×[厚み]約30mm×[高さ]約39mm                                                                                                                                                                                                                                                                                                                                                                                                                                                      |     |       |
| 入力    | AC100~240V・50/60Hz                                                                                                                                                                                                                                                                                                                                                                                                                                                                | 重量  | 約150g |
| 出力    | [単独接続時]<br>・USB Type-C1/C2ポート:65W(5V/3A,9V/3A,15V/3A,20V/3.25A)<br>PPS:52W(3.3V~16V/3.25A) QC:18W(5V/3A,9V/2A,12V/1.5A)<br>・USB-Aポート:18W(5V/3A,9V/2A,12V/1.5A)                                                                                                                                                                                                                                                                                                                    |     |       |
|       | [2ポート同時接続時]<br>・USB Type-C1ポート+USB Type-C2ポート:<br>USB Type-C1:45W(5V/3A,9V/3A,15V/3A,20V/2.25A)<br>PPS:45W(3.3V~16V/3A) QC:18W(5V/3A,9V/2A,12V/1.5A)<br>USB Type-C2:20W(5V/3A,9V/2A,12V/1.5A)<br>QC:18W(5V/3A,9V/2A,12V/1.5A)<br>・USB Type-C1ポート+USB-Aポート:<br>USB Type-C1:45W(5V/3A,9V/3A,15V/3A,20V/2.25A)<br>PPS:45W(3.3V~16V/3A) QC:18W(5V/3A,9V/2A,12V/1.5A)<br>USB-A:18W(5V/3A,9V/2A,12V/1.5A)<br>・USB Type-C2ポート+USB-Aポート:<br>USB Type-C2:7.5W(5V/1.5A) USB-A:7.5W(5V/1.5A) |     |       |
|       | [3ポート同時接続時]<br>・USB Type-C1:45W(5V/3A,9V/3A,15V/3A,20V/2.25A)<br>PPS:45W(3.3V~16V/3A) QC:18W(5V/3A,9V/2A,12V/1.5A)<br>USB Type-C2:7.5W(5V/1.5A) USB-A:7.5W(5V/1.5A)                                                                                                                                                                                                                                                                                                               |     |       |
| 使用温度  | 0℃~25℃                                                                                                                                                                                                                                                                                                                                                                                                                                                                            | 内容物 | 本体    |

## ご使用上の注意

**絵表示について** この取扱説明書および製品への表示では、製品を安全に正しくお使いいただき、あなたや他の人への危害や財産への損害を未然に防止するために、いろいろな絵表示をしています。その表示と意味は次のようになっています。内容をよく理解して本文をお読みください。

|  |                                                                             |
|--|-----------------------------------------------------------------------------|
|  | <b>警告</b> この表示を無視して、誤った取扱いをすると、人が死亡または重傷を負う可能性が想定される内容を示しています。              |
|  | <b>注意</b> この表示を無視して、誤った取扱いをすると、人が重傷を負う可能性が想定される内容および物的損害の発生が想定される内容を示しています。 |

安全にご利用いただくために、下記の注意事項を必ずお守りください。

## 警告

- 次のような場合には、直ちに使用をやめてご購入店もしくは弊社総合インフォメーションセンターにご相談ください。使用し続けると、火災や感電の原因となります。
  - ・煙が出ている、変なにおいや音がするといった異常が発生した場合
  - ・水に濡れた場合
  - ・本製品の内部に異物や液体が入った場合
  - ・ケーブル、電源プラグ、ケースが破損した場合
- 濡れた手で電源プラグ、ケーブルに触れないでください。火災や感電の原因となります。
- 本製品を日本国内以外のコンセントに接続しないでください。火災の原因となります。
- 電源プラグは、家庭用コンセントに奥までしっかりと挿し込んでご使用ください。挿し込みが不十分だと、接続不良などにより、火災や感電の原因となります。

## 注意

- 本製品を使用する前に、本体と接続端のコネクタ端子にほこり・液体などの異物がないか、十分に確認してください。特に、防水性能搭載の端末など、接続端末を濡らした際は、水分が付着していないかご注意ください。水濡れ充電、異物混入充電は、火災や感電、故障の原因となります。
- 本製品に端末機器を接続する際は、必ず本体機器の注意事項に従ってください。
- 本製品を次のような場所で使用・保管しないでください。火災、感電や故障の原因となります。
  - ・直射日光のあたる場所、暖房器具の近くなど、温度の高い場所
  - ・湿気が多い場所、水気のあるところ
  - ・ほこりの多い場所
  - ・振動の多い場所
- 本製品に非対応の充電ケーブルは使用しないでください。火災や溶解、故障の原因となります。

## 保証規定

- 保証期間  
1年間
- 保証対象  
保証対象は本製品の本体・本製品の動作に起因する部分のみとさせていただきます。取扱説明書および消耗品は対象外です。
- 保証内容  
1.弊社が定める保証期間(本製品ご購入日から起算されます。)内に、適切な使用環境で発生した本製品の故障に限り、無償で本製品を修理または交換いたします。※保証期間を超過している場合、有償となります。
- 無償保証範囲  
2. 以下の場合には、保証対象外となります。
  - (1) 購入証明書および故障した本製品をご提出いただけない場合。※購入証明書は、購入日、購入店、型番が確認できるもの(レシート・納品書など)を指します。
  - (2) 購入証明書に偽造・改変などが認められた場合。
  - (3) 中古品として本製品をご購入された場合。(リサイクルショップでの購入、オークション購入などで中古品を含む)
  - (4) 弊社および弊社が指定する機関以外の第三者ならびにお客様による改造、分解、修理により故障した場合。
  - (5) 弊社が定める機器以外に接続、または組み込んで使用し、故障または破損した場合。
  - (6) 通常一般家庭、一般オフィス内で想定される使用環境の範囲を超える温度、湿度、振動などにより故障した場合。
  - (7) 本製品をご購入いただいた後の輸送中に発生した衝撃、落下などにより故障した場合。
  - (8) 地震、火災、落雷、風水害、その他の天災地災、公害、異常電圧などの外的要因により故障した場合。
  - (9) 接続されている他の機器に起因して、本製品に故障、損傷が生じた場合。
  - (10) ソフトウェア(ファームウェア、ドライバ他)のアップデート作業によって故障、障害が生じた場合。
  - (11) 本製品の、パッケージ、取扱説明書、ならびに弊社ホームページ内などに記載の使用法、および注意に反する取り扱いによって生じた故障、損傷の場合。
  - (12) その他、無償修理または交換が認められない事由が発生した場合。

## ポート・ワット数

- ポート単独使用
  - ※C1 65W (PPS 52W) (QC 18W)
  - ※C2 65W (PPS 52W) (QC 18W)
  - ※A 18W


- 2ポート同時使用
  - 45W (PPS 45W) (QC 18W) 20W
  - 45W (PPS 45W) (QC 18W) 18W
  - 7.5W 7.5W

- 3ポート同時使用
  - 45W (PPS 45W) (QC 18W)
  - 7.5W 7.5W

※C1:USB Type-C1ポート ※C2:USB Type-C2ポート ※A:USB-Aポート

※本製品の温度上昇時など、状況によっては安全性保護のため出力を停止する場合があります。故障ではございませんので、1度本製品と接続機器の接続を切り、しばらく待ってから再度接続してください。※記載の出力値は本製品の性能値です。接続機器、OS/バージョン等の条件で実際の出力値は異なります。場合によっては充電時間が遅くなったり、充電できないことがあります。※接続機器の対応規格、ケーブルの仕様などにより充電出力は調整されます。最大出力での充電ができない場合があります。※接続機器の仕様、状態により、USB Power Delivery以外の規格での動作になる場合がございます。※イラストおよび画像はイメージです。実際の商品とは異なる場合がありますので、あらかじめご了承ください。※NINTENDO SWITCH™は、ドックでの利用に対応しておりません。※NINTENDO SWITCHは、任天堂株式会社の商標または登録商標です。※Lightningは米国およびその他の国で登録されたApple Inc.の商標です。※USB Type-C and USB-C are trademarks of USB Implementers Forum.


## Connection diagram



\* To connect this product, prepare the cable separately according to the device to be used.  
\* Your device may charge slower or not charge at all if connectors or cables that convert to terminals other than USB Type-C and Lightning are used.  
\* When another device is connected to an open port while this product is in use, the output of the connected port may temporarily drop and reconnect. When the smartphone starts charging, you will hear a sound. If you hear the same sound again, that is not a malfunction.

## How to use

- 1.Connect the charging cable to this product and connect the other end to the device you want to charge.
2. Pull out the prongs and plug the adapter into an outlet to start charging.



## Product specifications

|                             |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               |                  |           |
|-----------------------------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|------------------|-----------|
| Port shape                  | USB Type-C port x2, USB-A x1                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  |                  |           |
| Dimensions                  | (Width) approximately 66 x (depth) approximately 30 x (height) approximately 39 mm<br>(Width) approximately 2.6 x (depth) approximately 1.2 x (height) approximately 1.5 in.                                                                                                                                                                                                                                                                                                                                                                                                                                                                  |                  |           |
| Weight                      | Approximately 150 g / approximately 5.3 oz                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    |                  |           |
| Rated input                 | AC 100 V to 240 V, 50/60 Hz                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   |                  |           |
| Rated output                | [When connected to one device]<br>USB Type-C port 1/port 2:65 W (5 V/3 A, 9 V/3 A, 15 V/3 A, 20 V/3.25 A)<br>PPS:52 W(3.3 V to 16 V/3.25 A) QC:18 W(5 V/3 A, 9 V/2 A, 12 V/1.5 A)<br>USB-A port:18 W(5 V/3 A, 9 V/2 A, 12 V/1.5 A)                                                                                                                                                                                                                                                                                                                                                                                                            |                  |           |
|                             | [When connected to two ports simultaneously]<br>USB Type-C port 1 + USB Type-C port 2:<br>USB Type-C port 1:45 W(5 V/3 A, 9 V/3 A, 15 V/3 A, 20 V/2.25 A)<br>PPS:45 W(3.3 V to 16 V/3 A) QC:18 W(5 V/3 A, 9 V/2 A, 12 V/1.5 A)<br>USB Type-C port 2:20 W(5 V/3 A, 9 V/2.22 A)<br>QC:18 W(5 V/3 A, 9 V/2 A, 12 V/1.5 A)<br>USB Type-C port 1 + USB-A port:<br>USB Type-C port 1:45 W(5 V/3 A, 9 V/3 A, 15 V/3 A, 20 V/2.25 A)<br>PPS:45 W(3.3 V to 16 V/3 A) QC:18 W(5 V/3 A, 9 V/2 A, 12 V/1.5 A)<br>USB-A:18 W(5 V/3 A, 9 V/2 A, 12 V/1.5 A)<br>USB Type-C port 2 + USB-A port:<br>USB Type-C port 2:7.5 W(5 V/1.5 A) USB-A:7.5 W(5 V/1.5 A) |                  |           |
|                             | [When connected to three ports simultaneously]<br>USB Type-C port 1:45 W(5 V/3 A, 9 V/3 A, 15 V/3 A, 20 V/2.25 A)<br>PPS:45 W(3.3 V to 16 V/3 A) QC:18 W(5 V/3 A, 9 V/2 A, 12 V/1.5 A)<br>USB Type-C port 2:7.5 W(5 V/1.5 A) USB-A:7.5 W(5 V/1.5 A)                                                                                                                                                                                                                                                                                                                                                                                           |                  |           |
| Operating temperature range | 0 °C to 25 °C / 32 °F to 77 °F                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                | Package contents | Main unit |

## Precautions on use

**Regarding pictograms** The instructions in this manual and labels on this product use various pictograms to ensure the safe and correct use of this product and to prevent harm to you and other people as well as damage to property. These icons and their definitions are as follows. Please fully understand this before reading the main text.

|  |                                                                                                                      |
|--|----------------------------------------------------------------------------------------------------------------------|
|  | <b>WARNING</b> Ignoring these precautions may lead to erroneous handling that may cause death or serious injuries.   |
|  | <b>CAUTION</b> Ignoring these precautions may lead to erroneous handling that may cause serious injuries or damages. |

Be sure to observe the following precautions in order to ensure safe and correct use.

## WARNING

- Stop using the product immediately when smoke, abnormal odours or noises are coming from the product; when it is wet; when foreign matters or a liquid enters the product; when the cable, power plug, or case is damaged, and consult the store you purchased the product from. Doing otherwise may cause fire and electric shock.
- Do not touch the power plug or cable with wet hands. Doing so can cause a fire or electric shock.
- Do not connect this product to electrical outlets outside of Japan. It could cause fires.
- Firmly push the power plug all the way into a household outlet. A loose connection may result a fire or an electric shock.
- Do not forcibly pull or bend the cable, and do not place any heavy objects on it. Always hold the connector when plugging and unplugging the cable. It can cause armored cord damage, disconnection, and lead to a fire or electric shock.
- Do not overload outlets. Doing so can cause a fire.
- Do not attempt to disassemble or modify the product. Fire, electric shock or injuries may result.

## CAUTION

- Before using this product, check that there is no dust or liquid in the connectors of this device or the device to be connected. Check for the presence of water, especially if the connected water-proof device is wet. Charging when the connector is wet or has foreign matter in it may cause fires, electric shocks, or malfunctions.
- When connecting a device to the product, make sure to follow the precautions for that device.
- Do not use or store the product in the following places. Fire, electric shock or malfunctions may result.
  - In direct sunlight - In areas of high temperature such as in proximity to heating devices - In areas of high humidity - In wet or damp places - In dusty environments - In places with high levels of vibration
- Do not use this device with incompatible charging cables. It will cause fire, melting, or malfunctions.

## Compliance Status

|                                                                                                                                                                                                                                                                                     |                                                                                                    |                                                                                                                                |
|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|----------------------------------------------------------------------------------------------------|--------------------------------------------------------------------------------------------------------------------------------|
| This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation. | <a href="http://www.elecom.co.jp/global/certification/">www.elecom.co.jp/global/certification/</a> | <b>Responsible party</b><br>ELECOM USA, Inc.<br>4041 MacArthur Blvd Suite 400,<br>Newport Beach, CA 92660 USA<br>elecomusa.com |
|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|----------------------------------------------------------------------------------------------------|--------------------------------------------------------------------------------------------------------------------------------|

In order to make improvements to this product, the design and specifications are subject to change without prior notice.

### Trademark and name of the manufacturer:

## ELECOM CO., LTD.

Fushimimachi 4-1-1, Chuo-ku, Osaka City  
www.elecom.co.jp/global/

- \* In order to make improvements to this product and for improved safety, the design and specifications are subject to change without prior notice.
- \* The company and product names on the packaging are, in general, trademarks or registered trademarks of their respective companies.
- \* ELECOM CO., LTD. owns the copyright of this manual.
- \* Unauthorised copying and/or reproducing of all or part of this manual is prohibited.
- \* If you have any suggestions or doubts about this Manual, please contact your dealer.
- \* The specifications and appearance of this product may be changed without prior notice for product improvement purposes.
- \* When exporting this product, check the export regulations for the country of origin.

## Global Support



<https://www.elecom.co.jp/r/s536>

A customer who purchases outside Japan should contact the local retailer in the country of purchase for inquiries. In "ELECOM CO., LTD. (Japan)", no customer support is available for inquiries about purchases or usage in/from any countries other than Japan. Also, no foreign language other than Japanese is available. Replacements will be made under stipulation of the Elecom warranty.

Adapter Manual, Safety precautions, and Compliance with regulations  
1st edition, September 1, 2023  
**ELECOM**  
©2023 ELECOM Co., Ltd. All Rights Reserved.  
MSC-EC-AC6465\_0208\_ver.111