

Product number : LBT-OH05

ENGLISH

Manual

Bluetooth Wireless Headset

Bluetooth Ver.4.0

Package Contents

Basic Specifications

List of Main Operations

- Headset x 1
- USB charger cable x 1
- Manual x 1

- Safety precautions x 1
- Compliance with regulations x 1

Bluetooth® specifications	Bluetooth Ver.4.0												
Carrier frequency	2.4 GHz												
Spread spectrum	FHSS (Frequency Hopping Spread Spectrum)												
Transmission distance	Maximum radius of 100m (without obstacles)												
Supported profiles	A2DP (Advanced Audio Distribution Profile) AVRCP (Audio/Video Remote Control Profile) HSP (Headset Profile) HFP (Handsfree Profile)												
Compatible codec	SBC, AAC (automatic connection during pairing)												
SCMS-T	Supported												
Number of allowable paired devices	8												
Continuous standby time	Max. 300 hours												
Music playback/continuous conversation time	SBC ~ 16 hours; AAC ~ 14 hours; conversation ~ 15 hours												
Environmental conditions	<table><tr><th>In operation</th><th>Temperature</th><th>Humidity</th></tr><tr><td></td><td>20% to 80% (without condensation)</td><td>5°C to 35°C</td></tr><tr><th>In storage</th><th>Temperature</th><th>Humidity</th></tr><tr><td></td><td>20% to 80% (without condensation)</td><td>-10°C to +50°C</td></tr></table>	In operation	Temperature	Humidity		20% to 80% (without condensation)	5°C to 35°C	In storage	Temperature	Humidity		20% to 80% (without condensation)	-10°C to +50°C
In operation	Temperature	Humidity											
	20% to 80% (without condensation)	5°C to 35°C											
In storage	Temperature	Humidity											
	20% to 80% (without condensation)	-10°C to +50°C											
Dimensions (W x D x H)	Approx. 180 x 65 x 185 mm (excluding protrusions)												
Weight	Approx. 100 g (headset only)												

Function/State	Operation	LED light 1 (blue)	LED light 2 (red, green, orange)
Power on	With the power off, press the power button.	Off → Lights in blue for 2 seconds	—
Power off	With the power on, press the power button.	Lights in blue for 2 seconds → Off	—
Pairing mode	After turning the power on, press and hold the power button for 3 seconds.	Blinks in red and blue alternately	—
Connected	—	Blinks in blue once every 10 seconds	—
Disconnected	—	Blinks in blue once every 2 seconds	—
Receiving/ending calls	When receiving a call/during a call, quickly press the multi-function button once.	—	—
Charging	—	—	Turns on in red
Fully charged	—	—	Turns on in green
Remaining battery charge insufficient	—	—	Blinks two times in red once every minute
Volume adjustment	Quickly press the volume adjustment/previous button (← or →)	—	—
Pausing playback	Quickly press the multi-function button once.	—	—
Previous/next song	Press and hold the volume adjustment/next/previous button (← or →) for 3 seconds.	—	—

Name and Function of Each Part

8 Left
7 Right
* The side with the operation buttons is the right side.

When folded

1 2 3 4 5 6 7

1.Power button

2.Multi-function button

3.Volume adjustment/next/previous button

4.LED light 1

5.LED light 2

6.Microphone for calls

7.Micro USB charger connector

8.NFC antenna

Turns power on/off and performs pairing.

Plays/pauses music and receives/places calls.

To increase the volume: Press **+**. To decrease the volume: Press **-**. Next track: Press and hold **+** during playback or when playback is paused. Previous track: Press and hold **-** during playback or when playback is paused.

Indicates the power and pairing status in blue.

Indicates the power and pairing status in red, green, and orange.

For handsfree use.

Connect the included USB charger cable to charge the headset.

Pairing is possible by just touching the headset with an NFC-supported smartphone. (The antenna is within the left side of the headset.)

1 Charging the headset

2 Pairing

1 Connect the USB charger cable to the headset and a PC.

2 LED light 2 turns on in green when charging is complete.

1 Enable the pairing mode.

2 Search for this product (OH05) from the connected device.

3 Register this product (OH05) on the connected device.

Once charging starts, the LED light 2 will turn on in red. (A full charge takes approximately 2 hours.)

When LED light 1 switches to blinking slowly in blue (blinking once every 10 seconds), the pairing is complete.

This product supports a music streaming function (A2DP). You can listen to music or navigation voices played on connected mobile phones and smartphones. SCMS-T content protection is also supported.

Required Information for Connection

● Device name OH05

● Pass code 0000 (4 zeros)

3 Connection and Basic Operations

1 Check the connection.

2 The settings are complete.

Subsequent Connections

1 To turn on the headset

2 To turn off the headset

Listening to Music

1 Playing/pausing music

2 Adjusting the volume

3 Previous/next song

Talking

1 Receiving calls

2 Ending calls

3 Placing calls

<Operation examples>
iPhone
Place the call, and then select this product (OH05) for the audio output destination.
Android
Place the call, and then tap "Bluetooth" on the screen.
* The method used to switch the output destination after placing the call varies depending on the connected mobile phone.

Multipoint Function
The multipoint function enables you to use one headset to receive calls from two mobile phones.
1 Multipoint pairing procedure
1 Perform pairing with, and establish a connection to, the first device.
2 Disconnect from this device, and then set the headset to pairing mode again.
3 Perform pairing with, and establish a connection to, the second device.
4 Temporarily turn off the Bluetooth function on all the devices, turn on the (two) devices to connect to, then turn on the headset to reconnect the devices.

NFC Pairing (Simple Touch Pairing)

With a simple touch, this headset can be paired with NFC-enabled Android smartphones.

Left side of the headset

Back of the smartphone (Touch the product to the smartphone close to the NFC mark.)

Turn on the product. Turn on the NFC function on the smartphone, and then start the procedure.
1. Go to the Home screen on your smartphone.
2. Hold the smartphone's NFC antenna near the NFC antenna on the left side of the headset. Keep the devices next to each other during the NFC pairing process, until the connection is established.
A message similar to "Are you sure you want to pair the device?" is displayed on the screen.
3. Select "Yes".
4. After a short time, pairing is completed automatically and the connection is established.

한국어

취급설명서

블루투스 무선 헤드셋

Bluetooth Ver.4.0

패키지 내용 확인

기본 사양

주요 조작 일람표

- 헤드셋 본체 x1
- USB 충전 케이블 x1
- 취급설명서 x1

- 안전 조치 x1
- 규칙 준수 x1

블루투스 사양	Bluetooth® Ver.4.0								
반송파 주파수	2.4GHz 대								
주파수 확산 방식	FHSS (Frequency Hopping Spread Spectrum)								
전송 거리	최대 반경 약 100m (장애물이 없는 경우)								
지원 프로파일	A2DP (Advanced Audio Distribution Profile) AVRCP (Audio/Video Remote Control Profile) HSP (Headset Profile) HFP (Handsfree Profile)								
대용 코덱	SBC, AAC (페어링 시, 자동전송)								
SCMS-T	대응								
허용 동시장치 대수	8 대								
연속 대기시간	최대 300 시간								
음악 재생/연속 통화 시간	SBC: 16 시간, AAC: 14 시간 / 통화: 15 시간								
환경조건	<table><tr><th>작동 시</th><th>온도</th></tr><tr><td>습도</td><td>20%~80% (단, 결로현상이 없는 곳)</td></tr><tr><th>보관 시</th><th>온도</th></tr><tr><td>습도</td><td>-10°C ~ 50°C</td></tr></table>	작동 시	온도	습도	20%~80% (단, 결로현상이 없는 곳)	보관 시	온도	습도	-10°C ~ 50°C
작동 시	온도								
습도	20%~80% (단, 결로현상이 없는 곳)								
보관 시	온도								
습도	-10°C ~ 50°C								
외형 치수 (폭 x 깊이 x 높이)	약 180 x 65 x 185 mm (돌기부 제외) / 약 100g (본체만)								

기능 · 상태	조작	LED 램프 1 (청색)	LED 램프 2 (적색, 녹색, 주황색)
전원 ON	전원 OFF 시에 전원 버튼을 누른다	소등→청색으로 1 회 점멸	—
전원 OFF	전원 ON 시에 전원 버튼을 누른다	청색으로 2 초간 점등→소등	—
페어링 모드	전원 ON 후, 전원 버튼을 3 초 길게 누른다	적색과 청색 교대로 점멸	—
접속 상태	—	10 초마다 청색으로 1 회 점멸	—
비접속 상태	—	2 초마다 청색으로 1 회 점멸	—
전화발기 / 끊기	작신 시 / 통화시에 다기능 버튼을 짧게 1 회 누른다	—	—
충전중	—	—	적색으로 점등
충전 완료	—	—	녹색으로 점등
배터리 잔량부족	—	—	1분마다 적색으로 2 회 점멸
음량조절	음량조절 · 다음곡 / 이전곡 버튼 (← 또는 →) 을 짧게 1 회 누른다	—	—
일시정지	다기능 버튼을 짧게 1 회 누른다	—	—
다음곡 / 이전곡	음량조절 · 다음곡 / 이전곡 버튼 (← 또는 →) 을 3 초간 길게 누른다	—	—

각 부분의 명칭 및 기능

8 좌
7 우
※조작 버튼이 있는 쪽이 우측입니다.

접은 상태

1 2 3 4 5 6 7

1. 전원 버튼

2. 다기능 버튼

3. 음량조절 · 다음곡 / 이전곡 버튼

4. LED 램프 1

5. LED 램프 2

6. 통화용 마이크

7. micro USB 충전 커넥터

8. NFC 안테나

전원 ON/OFF, 페어링

재생 / 일시정지 수화 / 통화

음량을 크게 한다: **+** 를 누름
음량을 작게 한다: **-** 를 누름
다음곡: 음악재생 중 또는 일시정지 중에 **+** 를 짧게 누름
이전곡: 음악재생 중 또는 일시정지 중에 **-** 를 짧게 누름

청색으로 전원 및 페어링 상태를 나타낸다

적색, 녹색, 주황색으로 전원 및 페어링 상태를 나타낸다

핸즈프리로 사용한다

충전 시 부족 충전용 USB 케이블을 접속한다

NFC 를 탑재한 스마트폰에 터치하여 페어링 가능 (안테나는 좌측 헤드폰 안쪽)

1 충전하기

2 페어링

1 본 제품과 PC를 USB 충전 케이블로 접속

2 LED 램프 2가 녹색으로 점등하면 충전 완료

1 본 제품을 페어링 모드로 전환

2 접속한 기기에서 본 제품(OH05)을 검색

3 접속한 기기에 본 제품(OH05)을 등록

충전이 시작되면 LED 램프 2가 적색 점등합니다. (약 2시간이면 충전이 완료됩니다)

충전용 USB 케이블

본 제품의 다기능 버튼 OH05가 검색 화면에 표시되면 선택하여 등록합니다. LED 램프 1이 청색으로 천천히 점멸(10초에 1회 점멸)로 바뀌면 페어링 완료입니다.

본 제품을 페어링 모드로 전환

2 접속한 기기에 본 제품(OH05)을 검색

3 접속한 기기에 본 제품(OH05)을 등록

본 제품은 A2DP(오디오 프로파일) 지원으로, 접속한 휴대전화나 스마트폰의 음악 및 스마트폰의 내비게이션 음성 등을 들을 수 있으며, SCMS-T 방식의 콘텐츠 보호에도 대응하고 있습니다.

접속 시 필요한 정보입니다.

● 디바이스명 OH05

● 패스 코드 0000 (0 4개)

3 연결과 기본 조작

1 접속 확인

2 설정 완료

2회째 이후의 접속

전원 ON

전원 OFF

음악 듣기

1 음악 재생/일시정지

2 음량조절

3 다음곡/이전곡

통화하기

전화를 받는다

전화를 끊는다

발신한다

<조작 예>
iPhone인 경우
발신 후→음성 출력처에 본 제품(OH05)을 선택
Android인 경우
발신 후에 화면 내의 'Bluetooth' 버튼을 선택
※발신 후의 전환 방법은 접속한 휴대전화에 따라 다릅니다.

멀티포인트 기능
멀티포인트란 본 제품 1대로 2대의 휴대전화를 대기하는 기능입니다.
1 멀티포인트 페어링 순서
1 첫 번째 기기와 페어링, 접속한다
2 접속을 해제하고 헤드셋을 다시 페어링 모드로 전환한다
3 두 번째 기기와 페어링, 접속한다
4 일단 모든 기기의 블루투스 기능을 끄고 접속할 기기(2대), 헤드셋의 순서로 전원을 켜 후 재접속한다

NFC 페어링 (터치로 간단 페어링)

본 제품은 NFC를 탑재한 Android 스마트폰에 터치하여 페어링할 수 있습니다.

본 제품 좌측

스마트폰 뒷면 (NFC 마크 부근을 터치)

본 제품은 전원 ON, 스마트폰은 NFC 기능이 ON인 상태에서 조작을 시작하여 놓습니다.
1. 스마트폰을 홈 화면에 놓습니다.
2. 스마트폰 NFC 안테나 부분을 본 제품 좌 헤드폰의 NFC 안테나 부분에 가져옵니다. NFC 페어링을 시작할 경우, 접속이 완료될 때까지 가까이 두십시오. 화면에 '연결하겠습니까?'라는 메시지가 표시됩니다.
3. '네'를 선택합니다.
4. 잠시 후 자동으로 페어링 및 접속됩니다.

中文·简体

使用说明书

蓝牙耳机

Bluetooth Ver.4.0

确认包装内容

基本规格

主要操作列表

- 头戴式耳机本体 x1
- USB充电连接线 x1
- 使用说明书 x1

- 安全注意事项 x1
- 法规标示 x1

蓝牙规格	Bluetooth® Ver.4.0								
载波频率	2.4GHz 频段								
频率传输方式	FHSS (Frequency Hopping Spread Spectrum)								
传输距离	最大半径 约 100m (无阻碍物时)								
支持的协议	A2DP (Advanced Audio Distribution Profile) AVRCP (Audio/Video Remote Control Profile) HSP (Headset Profile) HFP (Handsfree Profile)								
支持的编解码格式	SBC, AAC (配对时自动连接)								
SCMS-T	支持								
可存储的配对设备数	8 台								
持续待机时间	最长 300 小时								
音乐播放/连续通话时间	SBC: 16 小时, AAC: 14 小时 / 通话: 15 小时								
环境条件	<table><tr><th>操作时</th><th>温度</th></tr><tr><td>湿度</td><td>20% ~ 80% (不结露)</td></tr><tr><th>存放时</th><th>温度</th></tr><tr><td>湿度</td><td>-10°C ~ +50°C</td></tr></table>	操作时	温度	湿度	20% ~ 80% (不结露)	存放时	温度	湿度	-10°C ~ +50°C
操作时	温度								
湿度	20% ~ 80% (不结露)								
存放时	温度								
湿度	-10°C ~ +50°C								
外形尺寸(宽 × 深 × 高)	约 180 x 65 x 185 mm (突出部除外)								
重量	约 100g (仅本体)								

功能 · 状态	操作	LED 灯 1 (蓝)	LED 灯 2 (红、绿、橙)
开启电源	电源关闭时接电源按钮	熄灯→蓝灯点亮 2 秒	—
关闭电源	电源接通时接电源按钮	蓝灯点亮 2 秒→熄灯	—
配对模式	电源接通后, 长按电源按钮 3 秒	红灯与蓝灯交替闪烁	—
连接状态	—	每 10 秒蓝灯闪烁 1 次	—
非连接状态	—	每 2 秒蓝灯闪烁 1 次	—
接听 / 挂断电话	接听时 / 通话时短按多功能按钮 1 次	—	—
充电中	—	—	红灯点亮
充电完成	—	—	绿灯点亮
电池剩余电量不足	—	—	每 1 分钟红灯闪烁 2 次
音量调整	短按音量调整, 下一首 / 上一首按钮 (← 或者 →) 1 次	—	—
暂停	短按多功能按钮 1 次	—	—
下一首 / 上一首	长按音量调整, 下一首 / 上一首按钮 (← 或者 →) 3 秒	—	—

各部分的名称及其作用

8 左
7 右
※有操作按钮的一边是右边。

折叠状态

1 2 3 4 5 6 7

1. 电源按钮

2. 多功能按钮

3. 音量调整 · 下一首 / 上一首按钮

4. LED 灯 1

5. LED 灯 2

6. 通话用麦克风

7. micro USB 充电转接头

8. NFC 感应区

电源的接通 / 关闭、配对

播放 / 暂停
接听电话 / 通话

调大音量: 按 **+**
调小音量: 按 **-**
下一首: 在音乐播放中或者暂停中长按 **+**
上一首: 在音乐播放中或者暂停中长按 **-**

以蓝色显示电源、配对状态

以红、绿、橙色显示电源、配对状态

以免提方式使用

充电时, 连接附带的 USB 充电转接头

本产品可与支持 NFC 功能的智能手机通过触碰进行配对。
(感应区位于左边耳机的里面)

1 预先充电

2 进行配对

1 以USB充电连接线连接本产品与计算机

2 LED灯2点亮绿色, 充电完成

1 将本产品置于配对模式

2 从连接设备上搜索本产品(OH05)

3 将本产品 (OH05) 登录到连接设备

充电开始后, LED灯2点亮呈红色。
(大约2小时后, 充电完成。)

LED灯2
充电中红灯点亮。
充电结束后, 绿灯点亮。

本产品设备名 "OH05" 将显示在搜索页面中, 选择并登录本产品。
LED灯1变为蓝色缓慢闪烁 (10秒闪烁1次), 配对完成。

连接时所需的信息

● 设备名 OH05

● 密码 0000 (4个零)

3 连接与基本操作

1 确认连接

2 设置完成

第2次及以后的连接

打开电源

关闭电源

听音乐

1 音乐的播放/暂停

2 调整音量

下一首/上一首

通话

接听电话

挂断电话

拨打电话

<操作例子>
使用iPhone时
拨打后→为语音输出目标选择本产品 (OH05)
使用Android时
拨打后, 按画面内的 "Bluetooth" 键。
※拨打后的切换方法取决于连接的手机。

多点功能
多点是指1台本产品可待机2台手机的功能。
1 多点的配对步骤
1 与第一台设备配对、连接。
2 解除连接, 将头戴式耳机再次设为配对模式。
3 与第二台设备配对、连接。
4 先关闭所有设备的蓝牙功能, 按照连接的设备 (2台) · 头戴式耳机的顺序打开电源, 再次连接。

NFC配对 (通过触碰, 轻松配对)

本产品可与搭载有NFC的Android智能手机通过触碰进行配对。

本产品左边

智能手机背面 (触摸NFC标志附近)

在本产品电源接通、智能手机的NFC功能打开的状态下开始操作。
1. 使智能手机返回至主画面。
2. 将智能手机的NFC感应区域靠近本产品左边耳机的NFC感应区, 进行NFC配对时, 在连接成功前请勿移开设备。
画面显示例如 "是否进行连接" 的信息。
3. 选择 "是"。
4. 稍等片刻配对将自动完成, 并连接。

